

Press release

Easy to build in, ready for Bluetooth Mesh (SIG): the new SENSOTEC NET generation. Our most innovative sensors network wirelessly via a Bluetooth Mesh network, can be configured via an app, control LED drivers via the DALI bus and are also supplied with energy by the DALI bus. Simple, flexible, quick to install.

New, smart sensors for recessed and surface-mounted installation - SENSOTEC makes your luminaire fit for the future. The sensor modules are designed as DALI-2 application controllers and can be connected directly to the DALI bus with just two cables. All sensors can be configured via Bluetooth and are networked via a Bluetooth mesh network. The sensors can of course also be used in all other sectors - from the lighting, sanitary, HVAC and other industries.


The advantages:

- Wireless networking without modifications to existing wiring (e.g. for retrofit applications, old luminaires out - new ones in), i.e. retrofitting possible without modifications to existing installations
- Small designs for optimum integration in narrow luminaires
- Power supply via the DALI bus requires no additional control gear in the luminaires
- High-frequency technology allows the sensors to be optically concealed and offers high IP protection or van dalen protection
- Proven STEINEL sensor technology integrated.
- The sensors are commissioned and configured using the Bluetooth Mesh app
- Free definition of luminaire groups with configurable behavior
- Wireless firmware updates for the entire network

HF2 NET




The HF2 NET is a Radar sensor module designed for built-in applications. Detection takes place through glass and non-metallic materials so that the modules can be used inside luminaires or other applications without any problems.



PIR NET



Small. Flat. Compact. Inconspicuous presence detector. 360° passive infrared sensor IR with a presence range of 4 x 4m (presence and radial) or 6 x 6m (tangential). With patented multi-segment pyrosensor lens.



Extension NET




The Extension NET is intended for a luminaire without sensors and is used to extend the Bluetooth Mesh network.

Two types, three connection variants - Our highbay sensors with installation heights of up to 14 meters are available as HB PIR 3360 and HB PIR 345. They differ in their detection range and are each available in three connection variants: Intra, Zhaga and Wire. They are ideal for office, commercial, public buildings, industry and logistics applications (room heights from 2 to 14 meters).

HB PIR 3360 NET




Free from giddiness. Long reach. Highly precise 360° infrared sensor. For monitoring of up to 1000 sqm. Detection range Ø 18m.



HB PIR 345 NET



Monitoring at the highest level. Infrared motion detector for indoor use. Detection area 30 x 4m.



Both sensors are available in an intra version for luminaire installation, as well as with a Zhaga base or as a wire version for luminaire installation.

Intra



Wire



Zhaga



Technical details

| | HF2 NET | PIR NET | Extension NET |
|-------------------------|--|------------------------------|------------------------------|
| Type | 9017 | 9018 | 9020 |
| Dimensions | 52 × 40.5 × 29.2mm | 66.4 × 20.4 × 18.5mm | 47 × 29 × 20mm |
| | Snap-in distance 61mm | Hole spacing 35mm | Hole spacing 55mm |
| | 3D data available on request | 3D data available on request | 3D data available on request |
| Equipment | Motion sensor | Motion sensor | - |
| | Light sensor | Light sensor | - |
| | Feedback display | Feedback display | Feedback display |
| | Parameterization interface | Parameterization interface | Parameterization interface |
| Sensor technology | High-frequency technology Rod antenna | Passive infrared technology | - |
| Transmission power | 1-2mW | - | - |
| Transmission frequency | 5.8GHz | - | - |
| Light measurement range | 2 - 2000lx | 2 - 2000lx | 2 - 2000lx |
| Angle of coverage | 360° with 160° opening angle | | |
| Mounting height | 2.5 - 3.5m | 2.0 - 5.0 m | |
| Optimum mounting height | 2.8m | 2.8m | |
| Radial range | 8m (50m ²) | 4 x 4m (16m ²) | |
| Tangential range | 8m (50m ²) | 6 x 6m (36m ²) | |
| Connection | 0.34 - 0.75mm ² | 0.34 - 0.75mm ² | 0.34 - 0.75mm ² |
| Protection class | IP20 | IP20 | IP20 |
| Temperature range | -20 to +60°C | -25 to +55°C | -25 to +60°C |
| Interfaces | DALI, Bluetooth | DALI, Bluetooth | DALI, Bluetooth |
| Conformity | CE | CE | CE |
| Standards | EN 61347-1 | EN 61347-1 | EN 61347-1 |
| | EN 61347-2-11 | EN 61347-2-11 | EN 61347-2-11 |
| | EN 55015 | EN 55015 | EN 55015 |
| | EN 61547 | EN 61547 | EN 61547 |
| | EN 301 489-1 EN 300 440 | EN 301 489-1 | EN 301 489-1 |

Highbay Sensors

| | HB PIR 345 NET Intra | HB PIR 345 NET Wire | HB PIR 345 NET Zhaga |
|-------------------------|---|--|---|
| Type | 9015 | 9024 | 9023 |
| Dimensions | 91.5 × 63.3 × 49mm 3D data available on request | 91.5 × 63.3 × 49mm Connecting wires 250mm (L) 3D data available on request | 91.5 × 63.3 × 57mm 3D data available on request |
| Equipment | Motion sensor Light sensor Feedback display Parameterization interface | Motion sensor Light sensor Feedback display Parameterization interface | Motion sensor Light sensor Feedback display Parameterization interface |
| Sensor technology | High-frequency technology | Passive infrared technology | Passive infrared technology |
| Transmission power | - | - | - |
| Transmission frequency | - | - | - |
| Light measurement range | 2 - 2000lx | 2 - 2000lx | 2 - 2000lx |
| Mounting height | 4 - 14m | 4 - 14m | 4 - 14m |
| Optimum mounting height | 12m | 12m | 12m |
| Radial reach | 30 x 4m (120m ²) | 30 x 4m (120m ²) | 30 x 4m (120m ²) |
| Tangential reach | 30 x 4m (120m ²) | 30 x 4m (120m ²) | 30 x 4m (120m ²) |
| Connection | 0.34 - 0.75mm ² | stranded wires | Zhaga |
| Protection class | IP20 / IP65* *Sealed lens | IP65 | IP65 |
| Temperature range | -20 to +50°C | -20 to +50°C | -20 to +50°C |
| Interfaces | DALI, Bluetooth | DALI, Bluetooth | DALI, Bluetooth |
| Conformity | CE | CE | CE |
| Standards | EN 613347-1 EN 61347-2-11 EN 55015 EN 61547 EN 301 489-1 | EN 613347-1 EN 61347-2-11 EN 55015 EN 61547 EN 301 489-1 | EN 613347-1 EN 61347-2-11 EN 55015 EN 61547 EN 301 489-1 |

| | HB PIR 3360 NET Intra | HB PIR 3360 NET Wire | HB PIR 3360 NET Zhaga |
|--|---|--|---|
| Type | 9016 | 9022 | 9021 |
| Dimensions | 91.5 × 63.3 × 49mm | 91.5 × 63.3 × 49mm Connecting wires 250mm (L) 3D data available on request | 91.5 × 63.3 × 57mm 3D data available on request |
| Equipment | Motion sensor Light sensor Feedback display Parameterization interface | Motion sensor Light sensor Feedback display Parameterization interface | Motion sensor Light sensor Feedback display Parameterization interface |
| Sensor technology | High-frequency technology | Passive infrared technology | High-frequency technology |
| Transmission power | - | - | - |
| Transmission frequency | - | - | - |
| Light measurement range | 2 - 2000lx | 2 - 2000lx | 2 - 2000lx |
| Mounting height | 4 - 14m | 4 - 14m | 4 - 14m |
| Optimum mounting height | 12m | 12m | 12m |
| Radial reach | 7m (38m ²) | 7m (38m ²) | 7m (38m ²) |
| Tangential reach | 18m (254m ²) | 18m (254m ²) | 18m (254m ²) |
| Connection | 0.34 - 0.75mm ² | stranded wires | Zhaga |
| Protection class | IP20 / IP65* *Sealed lens | IP65 | IP65 |
| Temperature range | -20 to +50°C | 20 to +50°C | 20 to +50°C |
| Interfaces | DALI, Bluetooth | DALI, Bluetooth | DALI, Bluetooth |
| Conformity | CE | CE | CE |
| Standards | EN 61347-1 EN 61347-2-11 EN 55015 EN 61547 EN 301 489-1 | EN 61347-1 EN 61347-2-11 EN 55015 EN 61547 EN 301 489-1 | EN 61347-1 EN 61347-2-11 EN 55015 EN 61547 EN 301 489-1 |
| Status: January 2021 (subject to change) | | | |

Outlook for Dialog Days 2021



At the STEINEL Dialog Days 2021, we will present the new SENSOTEC NET generation in a web seminar, the advantages and areas of application and show you SENSOTEC in use. At the end of the web seminar, we will answer your specific questions.

[Further information and registration](#)

Company portrait

As an OEM partner with 120 employees in Switzerland, STEINEL Solutions AG provides its customers with a service package comprising consulting, product development, industrialization, manufacturing and services from the idea to the finished product - in the spirit of a one-stop store. With sensor technology, communication, low power management and approval management as expertise in the field of development, the company develops customer-specific product applications and tailor-made solutions and counts both well-known market leaders and numerous hidden champions among its customers. Thanks to its affiliation with the STEINEL Group, STEINEL Solutions has access to a Europe-wide network. Depending on the product life cycle and market success, it is therefore possible to scale quickly and adequately and expand the series assembly of large-volume products to other locations.

With the SENSOTEC portfolio from STEINEL Solutions AG, luminaire and product manufacturers now have a flexible and easy-to-install solution for equipping products with smart and precise sensor intelligence without having to compromise on design.



**Do you have any questions about our SENSOTEC portfolio?
Our experts will be happy to help you!**

Andrea Lachner
OEM sales and expert in SENSOTEC

T + 41 (0) 55 418 23 99

sensotec@steinel.ch

www.steinel.ch