LED floodlight without sensor

XLED ONE XL

EAN 4007841 065232 Article number 065232







3000 K

















3 years

long life LED 50.000 h

3000K warm-white

IP44

180° vertical

Indoor/Outdoor

CE

manufacture's

Function description

Powerful lighting very big on style. The XLED ONE XL with an output of 42,6 W delivers a powerful 3000 K and of warm white light. Tilting through 180°, the wall and ceiling spot is fitted with high-quality and particularly long-lasting LEDs with a service life of a good 30 years - without any ifs or buts. Protection class: IP44.

Technical specifications

| Dimensions (L x W x H) | 193 x 259 x 215 mm |
|-------------------------|--------------------------------|
| With lamp | Yes, STEINEL LED system |
| With motion detector | No |
| Manufacturer's Warranty | 3 years |
| Version | white |
| PU1, EAN | 4007841065232 |
| Application, place | Outdoors |
| Application, room | outdoors, courtyard & driveway |
| Installation site | wall, ceiling |
| Installation | Wall, Ceiling, Surface wiring |
| Impact resistance | IK03 |
| IP-rating | IP44 |
| Protection class | I |
| Ambient temperature | from -20 up to 40 °C |
| Housing material | Aluminium |
| Cover material | Glass transparent |
| | |

| Mains power supply | 220 – 240 V / 50 – 60 Hz |
|-----------------------------------------------|-------------------------------|
| Photo-cell controller | No |
| Luminous flux total product | 4200 lm |
| Total product efficiency | 99 lm/W |
| Colour temperature | 3000 K |
| Colour variation LED | SDCM3 |
| Lamp | LED cannot be replaced |
| LED life expectancy (max. °C) | 50000 h |
| Service life LED L70B50 (25°) | > 36000 h |
| Drop in luminous flux in accordance with LM80 | L70B10 |
| LED cooling system | Passive Thermo Control |
| Basic light level function | No |
| Output | 42,6 W |
| Colour Rendering Index CRI | = 80 |
| Product category | LED floodlight without sensor |


LED floodlight without sensor

XLED ONE XL

white EAN 4007841 065232 Article number 065232



Dimension Drawing



Circuit diagram

