

# Data sheet

SENSOTEC NET wireless Mesh

## Extension NET



Technology Partner **SILVAIR**



110075231      SENSOTEC Extension NET

Intended to use in luminaires without sensor, the Extension NET is used for extending the Bluetooth mesh network.



### Technical specifications

Bluetooth Device Name	STE EXT NET
Type	9020
Dimensions	47 × 29 × 20mm Hole spacing 55mm
3D data	available online
Features	Feedback indicator, Bluetooth mesh
Sensor technology	-
Commissioning	Silvair app
Transmitter power	-
Transmission frequency	-
Light measurement range	-
Angle of coverage	-
Mounting height	-
Optimum mounting height	-
Reach, radial	-
Reach, tangential	-
Connection	0.34 - 0.75mm <sup>2</sup>
Supply voltage / current consumption	12 - 22.5VDC / max. 46mA
IP rating	IP20
Temperature range	-25 to +60°C (tc +60°C)
Bluetooth Range	35m
Interfaces	Dali, Bluetooth
Approval marks / Conformity	CE
Standards	EN 61347-1 / EN 61347-2-11 / EN 55015 / EN 61547 / EN 301 489-1

Note: STEINEL Solutions AG hereby declares that the SENSOTEC NET products comply with Directive 2014/53/EU.  
The full text of the EU Declaration of Conformity is available at the following link: <https://bit.ly/3NvySr7>

### Downloads & further details

[Data sheet SENSOTEC NET](#)

[3D data](#)

[EU Declaration of Conformity](#)